

# **PRESENT STATUS OF THE DISTRIBUTED COMPUTER CONTROL SYSTEM FOR THE 1.8GEV SYNCHROTRON RADIATION SOURCE TSRF AT TOHOKU UNIVERSITY**

Noriichi KANAYA<sup>#</sup>, Shoji SUZUKI\*), Shigeru SATO\*), Masahiro KATOH,

Photon Factory

High Energy Accelerator Research Organization (KEK)

1-1, Oho, Tsukuba, 305-0801, Japan

\*) Department of Physics, Graduate School of Science, Tohoku University,

Aobaku, Sendai, 980-8578, Japan

## **Abstract**

The control system has been designed for the 1.8GeV synchrotron radiation source at Tohoku-University Synchrotron Radiation Facility (TSRF), Sendai-city, Japan. TSRF is a third-generation synchrotron radiation facility proposed at Tohoku University, Sendai, Japan. The control system comprises three physical layers: UNIX workstations, FDDI (Fiber Distributed Data Interface) high speed network, and VME based field bus. UNIX workstations are employed for the upper layer that provides process control and user interface implemented in Java. The FDDI provides a 100-Mbps, token-passing, dual-ring LAN using a fiber-optic link suitable for exchanging control data reliably. On the bottom layer, there are VME crates with high performance CPUs that are interconnected to the magnets, RF, Vacuum, beam-position monitors, wigglers/undulators, beamlines and related components of the storage ring for local process control. The present status of the TSRF control system is discussed.

## **1 INTRODUCTION**

TSRF (Tohoku-university Synchrotron Radiation Source Facility) is a new third generation synchrotron radiation source that is currently proposed at Tohoku University, Sendai, approximately 350km north of Tokyo, Japan. TSRF is planned to be constructed at the site of Laboratory of Nuclear Science, Tohoku University, where a 300MeV-Linac and 1.2GeV Stretcher Booster Ring are currently in operation for nuclear physics experiments[1]. By taking advantage of the existing facility, TSRF employs the Stretcher Booster Ring as the injector for the TSRF storage ring. This can greatly reduce construction cost for the TSRF generation synchrotron radiation source.

TSRF is designed to provide VUV-SX synchrotron radiation to the experimental hall where experiments such as VUV experiments, surface physics, soft x-ray lithography, microscopy and crystal structure analysis, will be simultaneously carried out. The high-power wiggler/ undulator beam lines are simultaneously in operation, producing very intense synchrotron radiation beams[2]. The high-power beam lines are distributed along the long circumference of the storage ring. TSRF has a 1.8GeV storage ring with a DBA(double-bend-achromat) type, third-generation storage ring with emittance of 4.9nm rad, and a circumference of 244m. TSRF has more than ten wigglers/undulators, and thirty beamlines for Soft X-ray and VUV experiments for research. The facility has the 1.2GeV Stretcher Booster Ring, has been already in operation for nuclear physics. By taking advantage of this Stretcher Booster Ring, it will be employed as the beam injector for the Synchrotron Radiation Storage Ring.

The control system has been designed for the 1.8GeV TSRF synchrotron radiation source in order to operate the storage ring, providing stable synchrotron radiation to users at the experimental hall, and to improve the performance of the storage ring. In this study, the design of the TSRF control system is discussed.

## **2 SYSTEM CONFIGURATION**

The control system provides two major operating modes at the users' request: multi-bunch beam operation and single-bunch beam operation for time-resolved experiments. In addition, the control system allows an operator to provide both (1) automatic setup-and-go operation of the accelerator for users' experiments and (2) machine-study operation with remote control of the accelerator system in order to improve the accelerator performance and to study accelerator physics.

---

<sup>#</sup> Email: [noriichi.kanaya@kek.jp](mailto:noriichi.kanaya@kek.jp)

The software system which comprises three layers based on a client-server model. In particular, software interfaces for the hardware have been designed with Java Remote Method Invocation (RMI) running under the distributed VME CPU modules on the network. By taking advantage of Java RMI's capability, many remote accesses are carried out easily without paying a lot of efforts for remote communication as if the remote equipment was residing on the local machine. Note that for very-time critical operation such as a high speed feedback loop, it is implemented in C in order to avoid any time delay caused by garbage collection in the Java environment.

On the top layer, there are Console Managers as clients for operator console management. At the bottom layer, there are Device Servers which actually interface between the physical hardware devices and servers at the upper layers. A Dispatcher is a server in the middle layer, which resides among Console Managers and Device Servers at the lowest level.

PCs are cost effective equipment as operator consoles running at the top layer. Five PCs running under WindowsNT are utilized as console devices with a 20-inch bit-map color display, and a trackball used as a pointing device; they are also connected to the network. Under normal operation, two consoles are assigned to storage ring control, and the other to the beam-transport-line, injection-pulse magnets, safety interlock system and the beamline control system. Man-machine interfaces, including graphics status displays, provide pull-down and pop-up menus which are organized in a tree structure. Each branch menu is utilized to specify a device and its parameters. The Console Manager always depicts the present status of the accelerator complex.

There are five UNIX workstations at the middle layer for managing VME crates that are utilized for process control. Automatic operation is to setup, in principle, the parameters to devices, such as the bending magnets and families of quadrupole magnets, and then to initiate them. This can be carried out by invoking commands defined in a command file, whose file name is specified by an automatic instruction message solicited by an operator. The workstations automatically carry out following procedures; (1)Standby-for-beam-injection, (2)Beam-Injection, (3)Beam-Acceleration, (4) Re-injection (to set up parameters for injection of the beam after automatically initializing magnets), and (5)Shutdown.

The UNIX workstations, VME crates and PCs are connected to the FDDI (Fiber Distributed Data Interface) high speed network. The FDDI provides a 100-Mbps, token-passing, dual-ring LAN using a fiber-optic link suitable for exchanging control data reliably.

On the bottom layer, there are VME crates with high performance CPUs that are interconnected to the magnets, RF, Vacuum, beam-position monitors,

wigglers/ undulators, beamlines and related components of the storage ring for local process control. VME modules in the crates carry out time-critical jobs for the accelerator components: during beam acceleration at the storage ring, a power supply for bending magnets of the storage ring, and power supplies for families of quadrupole magnets are automatically synchronized in order to keep the betatron values constant.

There is a shared memory table in which all of operational parameters of the accelerator complex are stored in the relevant data entries. The table is also mapped to the physical memory which can be referenced by any application process. The purpose of the table is to allow all application processes to utilize the operational parameters as well as the present status of the accelerator complex necessary for their specific operation without directly accessing actual physical devices [3].

There is an on-line database system. The host collects all operational data and control data of the accelerator components. The operational and control data have been automatically stored in the database system to retrieve later specific combinations of behaviors of the accelerator components.

The storage ring has a number of components and sensors to be controlled, including vacuum valves, interlock devices, cooling water flow sensors, fast/slow vacuum sensors, pneumatic-pressure sensors, atmosphere sensors, Open-Request signals from the storage ring /the experimental hall, vacuum pressure gauges of the storage ring and the beam lines, valve driving units. These components are controlled and monitored by a computer of the control system.

### **3 DIAGNOSTICS USING A DATABASE FOR THE SYNCHROTRON RADIATION SOURCE**

In general high energy accelerators comprise a large number of accelerator components and sensors to be controlled, including digital I/Os and analogue I/Os. The components involve a number of actuators, vacuum valves, cooling-water flow sensors, vacuum sensors, pneumatic-pressure sensors, atmosphere sensors, radiation-safety interlocks, vacuum-pressure gauges and valve-driving units.

TSRF has a diagnostic system for such complex accelerator components that provides important trace-back information regarding the physical behavior of its components. The diagnostic system allows the operators to easily diagnose the cause of a failure by retrieving operational information to reproduce the physical behavior that has occurred in the storage ring and beamlines.

The database management system employed

for the diagnostic system is Oracle 8. Operational information regarding the beam lines is automatically stored to the Database. The diagnostic system is the same system that has been already implemented at the 2.5GeV synchrotron radiation source at the Photon Factory, KEK, providing reliable operation. The diagnostic system allows finding out the cause of a failure that has occurred in the numerous accelerator components, providing valuable information regarding a faulty component and related physical components that would suggest the cause of a failure. Thus the operator at the control room can easily locate any faulty component, and recover the accelerator component quickly.

## 4 CONCLUSION

The present status of the control system is discussed for the 1.8GeV generation synchrotron radiation facility TSRF, Sendai-city, where a 300MeV Linac and 1.2GeV Stretcher Booster Ring are ready as the injector for the 1.8GeV storage ring. The control system comprises three layers, and is composed of workstations, VME crates and PCs which are connected to the high speed FDDI network. The control system provides automatic operation for users' experiments as well as machine-study operation to improve the accelerator performance and to study accelerator physics.

## 5 ACKNOWLEDGEMENT

The authors wish to express their gratitude to Prof.J.Kasagi, Laboratory of Nuclear Science (LNS), Prof.M.Watanabe,. Research Institute of Scientific Measurements, Tohoku University for their valuable discussions, the staffs of LNS and all working group members of the project for their assistance and cooperation.

## 6 REFERENCES

- [1] M.Oyamada et al.,Proc. of 10th Symp. on Accel. Sci.Tech.p463,1995 (in Japanese).
- [2] M.Katoh, S.Sato, S.Suzuki and T.Yamakawa,"Lattice Design of the Synchrotron Radiation Source at Tohoku University," Proc. of the 5th European Particle Accelerator Conference,Spain,June,1996.
- [3] N.Kanaya, S.Asaoka and H.Maezawa, "A Generic Model for Monitoring Operational Parameters of Accelerators by Heterogeneous Multiprocesses at the Photon Factory", XIV Int'l Conf. on High Energy Accelerators, July, 1992, Hamburg, Germany.
- [4] <http://hera.kek.jp/>